Mounting Channels

NOTE: Mounting channels may be assembled horizontally or vertically, as shown below. If mounting channels are to be used with DIN rails or grid straps, one channel nut for each DIN rail/grid strap must be inserted into each channel before channel is attached to enclosure, as shown below. If 36 inch or longer mounting channels are used with grid straps, the mounting channels must be inserted through the center slots of grid straps before attaching to enclosure, as shown.

Once mounting style has been determined, slide mounting channel over studs in rear of enclosure. Attach with M8 flanged nuts and torque to 50 in−lbs (6 Nm).

Enclosure

Enclosure Stud

Mounting Channel

M8 Flanged Nut (supplied with enclosure)

Grid Strap (order separately)

Mounting Channel

Channel Nut (supplied with DIN rail and grid strap accessories)

Mounting Channel