

Flush Mount Enclosures



Step 1: Cut hole in surface for mounting enclosure (see table for dimensions).

Step 2: Drill four (or six) .312 inch diameter holes in mounting surface. Use enclosure as the template to determine number of holes required and drilling locations.

Step 3: Fasten flush mount enclosure to mounting surface using M6 screws, flat washers, and hex nuts as shown.

Catalog No.	H ± .25	W ± .25
C-FM12126	12.94	12.94
C-FM16126	16.94	12.94
C-FM20166	20.94	16.94
C-FM20206	20.94	20.94
C-FM24208	24.94	20.94
C-FM24248	24.94	24.94
C-FM30248	30.94	24.94

